

C4:SHADE&BLINDS

Our powerful controller for almost any IoT, Building Automation or Industrial Automation task. Based on the Raspberry Pi® Compute Module 4 with 2/4/8GB build in RAM, 32 GB SD CARD and stable 12-48Vdc power supply, 1xEthernet, 2xUSB 2.0, 1xMini-HDMI. LINUX is preinstalled. Additional versions with preinstalled CODESYS® runtime or Node Red, OpenHAB,... available.

RESI-C4-A-4SB-xGB	Raspberry Pi CM4*	XT8 143x110x62mm	4xSB	4 Shades & Blinds	RELAY OUTPUT $\leq 30V=$ $\leq 250V\sim$ $\leq 6A$ $AgSnO_2$ 8xForm A with common supply+root
RESI-C4-A-8SB-xGB	Raspberry Pi CM4*	XT12 213x110x62mm	8xSB	8 Shades & Blinds	RELAY OUTPUT $\leq 30V=$ $\leq 250V\sim$ $\leq 6A$ $AgSnO_2$ 16xForm A with common supply+root
RESI-C4-A-10RI4SB-xGB	Raspberry Pi CM4*	XT8 143x110x62mm	10xRI	10 Digital Inputs	LOGIC INPUT $12...250V\sim=$ $\leq 1.8mA$
			4xSB	4 Shades & Blinds	RELAY OUTPUT $\leq 30V=$ $\leq 250V\sim$ $\leq 6A$ $AgSnO_2$ 8xForm A with common supply+root
RESI-C4-A-20RI8SB-xGB	Raspberry Pi CM4*	XT12 213x110x62mm	20xRI	20 Digital Inputs	LOGIC INPUT $12...250V\sim=$ $\leq 1.8mA$
			8xSB	8 Shades & Blinds	RELAY OUTPUT $\leq 30V=$ $\leq 250V\sim$ $\leq 6A$ $AgSnO_2$ 16xForm A with common supply+root