


# RESI-DALI+PS-ETH

Our powerful master gateway between DALI light bus and host. Host protocols: MODBUS/TCP or ASCII text socket. Host communication via Ethernet interface. Integrated, switchable DALI power supply with max. 250mA DALI output current. Communicate with DALI 1.0 ballasts or with DALI 2.0 control gears. Support of DALI device type DT8 for RGB and RGBW LED stripes. Configuration & test of DALI light system with our free software MODBUSConfigurator.



<div><div>HOST MODBUS/TCP CLIENT ASCII TEXT SOCKET</div><div>ETHERNET</div><div></div><div>DALI 1.0/2.0+POWER</div><div><div>DALI LIGHT NETWORK</div></div></div>	<div>DALI 1.0/2.0 Up to 64 ballasts or control gears</div>	<div>DALI CABLE Up to 300m DALI cable length</div>	<div>DALI BUS search &amp; initialize &amp; test a DALI network</div>	<div>internal, switchable DALI power supply</div>
	<div>Functionality DALI 1.0/2.0 master gateway to control DALI 1.0 ballasts and to communicate with DALI 2.0 control gears. Supports all DALI 1.0/2.0 commands and DALI DT6 and DT8 commands. Special support of eDALI commands.</div>	<div>Ethernet Web Server for IP V4 setup MODBUS/TCP or MODBUS/RTU via Ethernet or ASCII text protocol</div>	<div>DALI output current <math>\leq 250\text{mA}</math></div>	<div>1xETHERNET 10/100MBit RJ45</div>
	<div>MODBUSConfigurator free configuration software</div>	<div>DIN EN 50022 Snap-on for DIN-Rail or wall mounting</div>	<div>XT4 71.3x110x62mm</div>	<div>12-48V= Power supply</div>